



# AAP 3500





Frequency	Hz	50
Model	AAP 3500	


## SPECIFICATIONS


- 


**Fuel gauge**  
Fuel gauge is on the fuel tank
- 


**OHV**  
Over Head Valve easy to maintenance
- 


**Oil level alarm**  
When the oil level is low that the engine will not start.
- 

**AVR**  
AVR is a device often solid state, for controlling the output voltage of a generator.
- 

**Circuit Protector**  
Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.
- 

**Voltmeter**  
It is a gauge for out put voltage of generator set.
- 

**Choke System**  
When the cold weather, choke system aid to operate the engine
- 

**Dual Element air filter**
- 

**Large capacity fuel tank**  
15-25 L

# AAP 3500

## GENERATING SET

AC Rated Power	kW	2,50
	kVA	3,00
Maximum Power	kW	2,80
	kVA	3,50
AC Rated Current	AC Rated Current	10,00
Voltage	V	230
Frequency	Hz	50
Phase		1
Power Factor		0,80
Fuel Consumption	L/h.	1,10
Noise Level	dB(A)	76,00

## ENGINE

Speed	rpm	3000
Power	Hp	6,5
Cylinder No.		1,0
Cylinder Bulk	mL.	196
Fuel Type		Gasoline
Oil Capacity	L	0,6
Fuel Tank Capacity	L	15,0
Start Type		Rope

## DIMENSIONS

Width	mm.	605
Lenght	mm.	490
Height	mm.	490
Dry Weight	kg.	50,0